

NOVATEL

Dongle Installation for Windows

Plug the dongle, and wait for the Installation Wizard to start



Click Next





License Agreement window

Check I accept the terms in the license agreement Click Next

License Agreement			
Please read the following license agreem	ent carefully.		
Disclaimer and Limitation of Liab	ility		
Novatel Wireless, Inc. assumes no i resulting from the use of its products	responsibility for s.	any damage o	or loss
Novatel Wireless, Inc. assumes no i third parties, which may arise throug	responsibility for gh the use of its	any loss or cla products.	aims by
Novatel Wireless, Inc. assumes no n caused by deletion or loss of data a	responsibility for s a result of mal	any damage of function, or rep	or loss pairs. Be
 I accept the terms in the license agreeme 	ent		Print
\bigcirc I do not accept the terms in the license a	greement		
nstallShield			
	C Back	Nexts	Cancel

Ready to Install window Click Install

Ready to Install the Program The wizard is ready to begin installation.
Click Install to begin the installation.
If you want to review or change any of your installation settings, click Back. Click Cancel to exit the wizard.
Create desktop shortcut.
stallShield



Setup complete window

Click Finish and wait for the connection manager to start





NOVATEL conenction manager Click Unlock Enter PIN code



- **NOVATEL** Connection Manager
- Click on the icon in the top left menu
- Select Settings
- Click on **Profile Manager**



Profile Manager Window

Click New





In the Pop-Up window

- Profile name: Alfa 3G
- Carrier name: Alfa
- APN: internet.mic1.com.lb
- Authentication Type: **PAP**
- PDP Type: IP
- Dial String: *99#
- User Name: mic1
- Password: mic1
- Click **OK** and set the connection to default in the previous window
- Click OK

Profile Name:	3G
Carrier Name:	Alfa
APN:	internet.mic1.com.lb
Dial String:	*99#
PDP Type:	IP 🗸
Authentication Type:	PAP
Username:	mic1
Password	••••
Confirm Password	••••



NOVATEL connection manager

- Click on the icon in the top left menu
- Select Settings
- Click on Configuration



Configuration window

Choose the required network selection



Dashboard main page